

# In-Wall Smart Fan Control

BY  
JASCO®



## Model 14287 / ZW4002

### KEY FEATURES

- Turn ON/OFF and control speed level of the connected Ceiling fan manually or via Z-Wave remote control (On/Off, High, Medium, Low)
- May be used in single pole installation or with up to four GE model 12723 Add-on switches in 3, 4, 5 or 6-way wiring configurations
- Can be Included in multiple Groups and Scenes
- Supports Advanced Configuration; LED status, Invert switch (if unit is installed upside down)
- Screw Terminal installation; requires wiring connections for Line (Hot), Load, Neutral and Ground. Traveler wire required for multi pole installation
- Use a standard size wall plate for single gang installations (wall plate not included)
- Interchangeable Paddle switch: White & light almond paddle included in package
- LED can be enabled/disabled manually
- Inline traveler circuit protection

### SPECIFICATIONS

Power 120VAC, 60Hz

Signal (Frequency) 908.4/916 MHz

Maximum Fan Motor Load: 2.5A

Range: Up to 150 feet line of sight between the wireless controller and the closest Z-Wave receiver module

Operating Temperature: 32-104° F (0-40° C)

For Indoor Use Only

Control fan motor only, not intended for lighting control. No more than two fans

### REGULATORY CERTIFICATIONS



# In-Wall Smart Fan Control

BY  
JASCO®



**Model 14287 / ZW4002**

## Z-WAVE MANUFACTURER SPECIFIC INFORMATION

<https://products.z-wavealliance.org/products/2506>

Z-Wave Certification Number: ZC10-17075673

Manufacturer ID: 0x0063

Product Type ID: 0x4944

Product ID: 0x3131

## SUPPORTED COMMAND CLASSES

Supported Command Classes

- All Switch V1
- Association Group Information V1
- Association V2
- Basic V1
- Configuration V1
- CRC16 Encapsulation V1
- Device Reset Local V1
- Firmware Update MD V2
- Manufacturer Specific V2
- Powerlevel V1
- Scene Activation V1
- Scene Actuator Configuration V1
- Switch Multilevel V1
- Version V2
- Z-Wave Plus Info V2

Controlled Command Classes

- Basic V1

## MANUAL BUTTON PRESS FEATURES

### Functions

Invert LED

### Button Press Method

Quickly press up 3 times then press down 1 time

# In-Wall Smart Fan Control

BY  
JASCO®



**Model 14287 / ZW4002**

## ADJUSTABLE CONFIGURATIONS

PARAMETER			
Number	Size	Name	Values
4	1	Invert Switch	0 - (Default) 1 - Invert

## FACTORY RESET

Quickly press ON (Top) button three (3) times then immediately press the OFF button three (3) times. The LED will flash ON/OFF 5 times when completed successfully