

Plug-In Smart Switch with USB Charging

BY
JASCO®



Model 28177 / ZW4105

KEY FEATURES

- Remote Control
Turn ON/OFF connected lighting manually or via smartphone or tablet
- Multi-Purpose
2 USB Ultra Charge* ports (3.4A) are available on each side of the device
- Dual Outlets
Wirelessly control both outlets independently**
- Home Automation
Can be set up to control scenes or used in a scheduled event
- Built-in Z-Wave range extender
- OTA (Over-the-Air) Updateable
Utilizes the Z-Wave Firmware Update Meta Data command class for standardized wireless firmware updates

* Ultra Charge safely charges up to 40% faster than traditional 5.0V USB chargers. Results will vary by device & connected cable.

**Independent control requires hub with multi-channel support

SPECIFICATIONS

Power 120VAC, 60Hz

Signal (Frequency) 908.4/916 MHz

Maximum load (Total): 120VAC, 600W Incandescent, 1/2HP Motor, 1560W (13A) Resistive

USB Output: 5.2VDC MAX 2.4A each USB. MAX total 3.4A both USB

Range: Up to 150 feet line of sight between the wireless controller and the closest Z-Wave device

Operating Temperature: 32-104° F (0-40° C)

For Indoor Use Only

REGULATORY CERTIFICATIONS



Plug-In Smart Switch with USB Charging

BY
JASCO®



Model 28177 / ZW4105

Z-WAVE MANUFACTURER SPECIFIC INFORMATION

<http://products.z-wavealliance.org/products/2192>

Z-Wave Certification Number: ZC10-17025423

Manufacturer ID: 0x0063

Product Type ID: 0x5052

Product ID: 0x3132

SUPPORTED COMMAND CLASSES

Supported Command Classes

- All Switch V1
- Association Group Information V1
- Association V2
- Basic V1
- Configuration V1
- CRC16 Encapsulation V1
- Device Reset Local V1
- Firmware Update MD V2
- Manufacturer Specific V2
- Multi-Channel_V4
- Multi-Channel-Association_V2
- Powerlevel V1
- Scene Activation V1
- Scene Actuator Configuration V1
- Switch Binary V1
- Version V2
- Z-Wave Plus Info V2

Controlled Command Classes

- Basic V1

MANUAL BUTTON PRESS FEATURES

Functions

Invert LED: Change to LED ON when Device Off

Button Press Method

Press button 10 times quickly

Plug-In Smart Switch with USB Charging

BY JASCO®



Model 28177 / ZW4105

ADJUSTABLE CONFIGURATIONS

PARAMETER			
Number	Size	Name	Values
3	1	Adjust Button LED Light	0 - (Default) LED ON / Device OFF 1 - LED ON / Device ON 2 - Disable LED

FACTORY RESET

If plugged in, unplug from the receptacle. Press and hold the top button for at least 3 seconds while you plug the switch into the receptacle.