



Model 14291 / ZW4005

KEY FEATURES

- Turn the connected device On/Off manually or via Z-Wave remote control
- May be used in single pole installation or with up to four GE model 12723 Add-on switches in 3, 4, 5 or 6-way wiring configurations
- Blue LED indicates switch location in a dark room
- Can be Included in multiple Groups and Scenes
- Built-in Z-Wave range extender
- OTA Updateable
- Utilizes the Z-Wave Firmware Update Meta Data command class for standardized firmware updates Over the Air
- Supports Advanced Configuration; LED status, Invert switch (if unit is installed upside down)
- Screw Terminal installation; requires wiring connections for Line (Hot), Load, Neutral, and Ground. Traveler wire required for multi pole installation
- Use a standard-size wall plate for single gang installations (wall plate not included); Multi-gang box option available (removable 'side wings')
- Interchangeable Paddle switch: White & light almond paddle included in package
- LED can be enabled/disabled manually
- Inline traveler circuit protection
- Z-Wave Plus Certified

SPECIFICATIONS

Power 120VAC, 60Hz

Signal (Frequency) 908.4/916 MHz

Maximum Load: 960W Incandescent 1/2 HP Motor 1800W (15A) Resistive

Range: Up to 150 feet line of sight between the wireless controller and the closest Z-Wave receiver module

Operating Temperature: 32-104° F (0-40° C)

For Indoor Use Only

REGULATORY CERTIFICATIONS



In-Wall Smart Switch

BY
JASCO®



Model 14291 / ZW4005

Z-WAVE MANUFACTURER SPECIFIC INFORMATION

<https://products.z-wavealliance.org/products/2501>

Z-Wave Certification Number: ZC10-17075672

Manufacturer ID: 0x0063

Product Type ID: 0x4952

Product ID: 0x3130

SUPPORTED COMMAND CLASSES

Supported Command Classes

- All Switch V1
- Association Group Information V1
- Association V2
- Basic V1
- Configuration V1
- CRC16 Encapsulation V1
- Device Reset Local V1
- Firmware Update MD V2
- Manufacturer Specific V2
- Powerlevel V1
- Scene Activation V1
- Scene Actuator Configuration V1
- Switch Binary V1
- Version V2
- Z-Wave Plus Info V2

Controlled Command Classes

- Basic V1

MANUAL BUTTON PRESS FEATURES

Functions

Disable LED

Button Press Method

Quickly Press Up 3 Times Then Press Down 1 Time

In-Wall Smart Switch

BY JASCO®



Model 14291 / ZW4005

ADJUSTABLE CONFIGURATIONS

PARAMETER			
Number	Size	Name	Values
3	1	Invert LED	0 - LED ON / Device OFF 1 - LED ON / Device ON 2 - Disable LED
4	1	Invert Switch	0 - (Default) 1 - Invert

FACTORY RESET

Quickly press ON (Top) button three (3) times then immediately press the OFF button three (3) times. The LED will flash ON/OFF 5 times when completed successfully