

# In-Wall Smart Toggle Switch

BY  
JASCO®



**Model 14292 / ZW4003**

## KEY FEATURES

- Turn the connected device On/Off manually or via Z-Wave remote control.
- May be used in single pole installation or with up to four GE model 12728 (WH) or 12732 (LA) Add-on switches in 3, 4, 5 or 6-way wiring configurations
- Toggle style switch to match existing switches
- Can be included in multiple Groups and Scenes
- Built-in Z-Wave range extender
- OTA Updateable
  - o Utilizes the Z-Wave Firmware Update Meta Data command class for standardized firmware updates Over the Air
- Supports Advanced Configuration; Invert switch (if unit is installed upside down)
- Screw Terminal installation; requires wiring connections for Line (Hot), Load, Neutral, and Ground. Traveler wire required for multi pole installation
- Use a standard-size wall plate for single gang installations (wall plate not included); Multi-gang box option available (removable 'side wings')
- Inline traveler circuit protection
- Z-Wave Plus Certified

## SPECIFICATIONS

Power 120VAC, 60Hz

Signal (Frequency) 908.4/916 MHz

Maximum load: 960W Incandescent, 1/2 HP Motor or 1800W (15A) Resistive

Range: Up to 150 feet line of sight between the wireless controller and the closest Z-Wave device

Operating Temperature: 32-104° F (0-40° C)

Requires neutral wire

For Indoor Use Only

## REGULATORY CERTIFICATIONS



# In-Wall Smart Toggle Switch

BY  
JASCO®



**Model 14292 / ZW4003**

## Z-WAVE MANUFACTURER SPECIFIC INFORMATION

<http://products.z-wavealliance.org/products/2502>

Z-Wave Certification Number: ZC10-17075671

Manufacturer ID: 0x0063

Product Type ID: 0x4952

Product ID: 0x3037

## SUPPORTED COMMAND CLASSES

### Supported Command Classes

- All Switch V1
- Association Group Information V1
- Association V2
- Basic V1
- Configuration V1
- CRC16 Encapsulation V1
- Device Reset Local V1
- Firmware Update MD V2
- Manufacturer Specific V2
- Powerlevel V1
- Scene Activation V1
- Scene Actuator Configuration V1
- Switch Binary V1
- Version V2
- Z-Wave Plus Info V2

### Controlled Command Classes

- Basic V1

# In-Wall Smart Toggle Switch

BY JASCO®



Model 14292 / ZW4003

## MANUAL BUTTON PRESS FEATURES

Functions

N/A

Button Press Method

N/A

## ADJUSTABLE CONFIGURATIONS

PARAMETER			
Number	Size	Name	Values
4	1	Invert Switch	0 (Default) 1 - Invert Switch

## FACTORY RESET

Quickly press the ON button 3 times, then press the OFF button 3 times.