

Two Outlet Plug-In Smart Switch

BY
JASCO®



Model 14282 / ZW4106

KEY FEATURES

- Two Z-wave controlled AC outlets
 - o Both Outlets controlled together (Cannot be controlled independently)
 - o Remote ON/OFF control via the Z-Wave controller
 - o Manual ON/OFF control with the toppush-button
- Space efficient design
 - o Does not block the lower outlet when plugged in to the upper outlet of a duplex wall receptacle. (This assumes that the duplex receptacle is mounted with the ground pin down.)
 - o Plugs and cords for connected devices route to the side allowing close placement of furniture
- Built-in Z-Wave range extender
- OTA Updateable
 - o Utilizes the Z-Wave Firmware Update Meta Data command class for standardized firmware updates Over the Air
- Z-Wave Plus certified
- Two Toned coloring

SPECIFICATIONS

Power 120VAC, 60Hz

Signal (Frequency) 908.4/916 MHz

Maximum load for the Z-Wave controlled outlet: 600W (5A) Incandescent / 1/2 HP Motor or 1800W (15A) Resistive
Z-Wave controlled outlet is fused @ 5A. This fuse is not user serviceable

Range: Up to 150 feet line of sight between the wireless controller and the closest Z-Wave receiver module

Operating Temperature: 32-104 degree F (0-40 C)

For Indoor Use Only

REGULATORY CERTIFICATIONS



Two Outlet Plug-In Smart Switch

BY
JASCO®



Model 14282 / ZW4106

Z-WAVE MANUFACTURER SPECIFIC INFORMATION

<http://products.z-wavealliance.org/products/2104>

Z-Wave Certification Number: ZC10-16125337

Manufacturer ID: 0x0063

Product Type ID: 0x5052

Product ID: 0x3033

SUPPORTED COMMAND CLASSES

Supported Command Classes

- All Switch V1
- Association Group Information V1
- Association V2
- Basic V1
- Configuration V1
- CRC16 Encapsulation V1
- Device Reset Local V1
- Firmware Update MD V2
- Manufacturer Specific V2
- Powerlevel V1
- Scene Activation V1
- Scene Actuator Configuration V1
- Switch Binary V1
- Version V2
- Z-Wave Plus Info V2

Controlled Command Classes

- Basic V1

MANUAL BUTTON PRESS FEATURES

Functions

Invert LED: Change to LED ON when Device Off

Button Press Method

Press button 10 times quickly

Two Outlet Plug-In Smart Switch

BY JASCO®



Model 14282 / ZW4106

ADJUSTABLE CONFIGURATIONS

PARAMETER			
Number	Size	Name	Values
3	1	Adjust Button LED Light	0 - LED ON / Device OFF 1 - LED ON / Device ON 2 - Disable LED

FACTORY RESET

If plugged in, unplug from the receptacle. Press and hold the top button for at least 3 seconds while you plug the switch into the receptacle.